


LUX9512

The LUXIMA[™] LUX9512 image sensor is a 9.5 Megapixel 1,333 FPS Global Shutter CMOS Digital Sensor for applications in the 3D scanning, intraoral scanning, dental, motion analysis, laser triangulation, line profiling, and wafer inspection markets. It allows ease of integration and lower system noise with on-chip 12 bit ADC, and 128 parallel LVDS outputs. The sensor supports 8 simultaneous Region-Of-Interest readouts with flexible window positions. The user can obtain faster frame rates through X, Y windowing. Color and monochrome options are offered in a 696 pin LGA-LCC package with a footprint of 39.8 mm × 37.8 mm.



| Optical format | 2″ | |
|-----------------------------|--|-------------------|
| Active resolution | 4096 × 2304 pixels | |
| Pixel | 6.5 um pitch PPD global shutter pixel | |
| Full well | 12 Ke- | |
| Read noise | 8 e- | |
| Responsivity | 6.0 V/lux-sec @ 525nm without color filter | |
| High dynamic range mode | 3 slope HDR capability | |
| Frame rate | Resolution | Frame Rate |
| | 4096 × 2304 | 1,333 FPS |
| | 2048×1080 | 5,565 FPS |
| | 2048 x 512 | 11,631 FPS |
| | 2048 x 128 | 44,209 FPS |
| | 2048 x 64 | 82,919 FPS |
| | 2048 x 32 | 147,493 FPS |
| Region of interest | Windowing and up to 8 simultaneous ROI's are supported | |
| Binning | 2x2, 1x2, 2x1 | |
| Analog to digital converter | 12b on chip ADC | |
| Analog gain options | 1x - 6x | |
| Clock rate | 100 MHz maximum | |
| Number of data channels | 128 LVDS data channels + 8 LVDS synchronization channels Multiplexer mode: 64 LVDS or 32 LVDS data channels | |
| Output data rate | Bit Depth | Clock Rate 100MHz |
| | 12b | 1200 Mbps |
| | 10b | 1000 Mbps |
| | 8b | 800 Mbps |
| Power supply | 3.3V Analog, 1.8V Analog & 1.8V Digital | |
| Power consumption | 5.7W Typical | |
| - | Lower power with Multiplexer Mode | |
| Communication interface | 4-Wire serial peripheral interface (SPI) | |
| Package type | 696 pin LGA-LCC in a footprint of 39.8 mm × 37.8 mm | |
| Color filter | Color or Monochrome | |